


4D-Nucleofector® Next Generation Quick Guide

Prior to first use please read the manual provided with the USB stick or at www.lonza.com/new-4d-nucleofector and read the safety instructions carefully.

Installation of Units

1. Unpack the units
2. Connect the cables as shown
3. Switch on the device at the rear
4. Press the power button at the front


The core unit will automatically detect the functional units attached.



Starting an Experiment



1. Pick the vessel type you will use in your experiment by tapping on the vessel symbol (A)
2. Select the wells to define by tapping on the well or dragging across the screen for definition of more than one sample at once
 - Pick sample type (B)
 - Choose pulse code and solution or pick a predefined cell type code
 - Press "Deselect" to remove the selection
3. Press "Next" to see a summary of all defined wells (this step is only enabled if all selected samples are fully defined (Sample Type, Pulse Code and Solution))
4. Load the sample in the Nucleocuvette® Vessel
Press "Start" to run the experiment (C)




D

For 96-well Unit:

- Switch between plate view and strip view for more details
- In plate view select the wells and tap on edit to define the sample (D)

Using Predefined and Saved Experiments



E

1. Tap on the accordion symbol in the left top corner of the home screen
2. Select "Experiment"
3. Find the experiment by scrolling the screen or using the arrows at the right side
4. Choose the experiment by tapping in the checkmark box beside the experiment name (E)

F


5. Press "Load" (F)
6. Check the conditions defined and press "Next" to see a summary of all defined wells



G

7. Load the sample
8. Press "Start" to run the experiment (G)


The Home Screen



H

1. You can reach the home screen any time by tapping on the accordion menu and selecting Home (H)
2. You can start a new experiment by tapping on the vessel type
3. Load experiments by selecting "Top experiments"
4. Change the settings by tapping on the gear symbol in the upper right corner and selecting "Settings"

System Settings



1. By tapping the gear symbol and selecting “Settings” (I), the system settings screen is shown
 - Change time and date or time and date format (J)
 - Adjust display brightness (K)
 - Adjust volume or mute sound (L)
 - Select “Experiment autonaming” to automatically name the experiment with date and time created (M)
 - Check for Network (N)
 - Receive information on Firmware version (O)
2. “Open and Close Drawer” are only visible if a vessel was selected before tapping on the gear icon.
3. Shutdown will apply the transportation lock (only if not unselected in settings menu) and safely shutdown the 4D-Nucleofactor® System

For detailed information download the manual at www.lonza.com/new-4d-nucleofactor or find it on the USB stick provided with this device.

Contact Us

North America

Customer Service: + 1 800 638 8174 (toll free)
order.us@lonza.com
Scientific Support: + 1 800 521 0390 (toll free)
scientific.support@lonza.com

Europe

Customer Service: + 32 87 321 611
order.europe@lonza.com
Scientific Support: + 32 87 321 611
scientific.support.eu@lonza.com

International

Contact your local Lonza Distributor
Customer Service: + 1 301 898 7025
Fax: + 1 301 845 8291
scientific.support@lonza.com

Lonza Cologne GmbH – 50829 Cologne Germany

The Nucleofector® Technology is covered by patent and/or patent pending rights owned by the Lonza Group Ltd or its affiliates.

All trademarks belong to Lonza, registered in USA, EU or CH or to third party owners and used only for informational purposes. The information contained herein is believed to be correct and corresponds to the latest state of scientific and technical knowledge. However, no warranty is made, either expressed or implied, regarding its accuracy or the results to be obtained from the use of such information and no warranty is expressed or implied concerning the use of these products. The buyer assumes all risks of use and/or handling. Any user must make his own determination and satisfy himself that the products supplied by Lonza Group Ltd or its affiliates and the information and recommendations given by Lonza Group Ltd or its affiliates are (i) suitable for intended process or purpose, (ii) in compliance with environmental, health and safety regulations, and (iii) will not infringe any third party's intellectual property rights. The user bears the sole responsibility for determining the existence of any such third party rights, as well as obtaining any necessary licenses. For more details: www.lonza.com/legal.